

Cl6 should be 0.01μ F

The wave band switch (SIa-SIg) is shown in the long wave position and is drawn as seen from the rear; rotate clockwise for medium, short, and gramophone. The black contacts and inner rotors are on the hidden sides of the wafers and the lugs marked with a cross are the nearer to the chassis. Blank positions and anchoring tags are shown by a spot.

Circuit voltages are shown within rectangles and were measured with a $20 \text{K}\Omega/\text{V}$ meter while the receiver was switched to the M band. Two readings are quoted for those points where the voltage differs appreciably from No-Signal

(N.S.) to Strong-Signal (S.S.) conditions.

Where the resistance of a coil is less than one ohm, the value is omitted. Component terminals and connecting leads are identified by test point (t.p.) numbers which correspond with those appearing on the chassis drawings.

The valve pin numbers are shown within small circles.

Squegging. If squegging occurs when fitting a new frequency changer valve, a 39Ω resistor (Part No. 24389) should be added in series with C23, and C22 changed to 82pF (Part No. 28179).